




# BlackBerry 7510 Logic Board Replacement

Written By: Neil Johnson



---

## INTRODUCTION

This is a guide on how to replace the logic board on your BlackBerry 7510.



### TOOLS:

- [T6 Torx Screwdriver](#) (1)
-

## Step 1 — Back Face of Phone



- ❗ Remove the battery cover and battery before continuing.
- Remove the six T6 Torx screws on the back of the phone.
- Make sure to keep the screws somewhere that they will not get lost.

## Step 2



- Using your finger nail or a spudger, carefully pry up the back cover.
- Begin in one spot and slowly circle around the device as you pry up all of the back cover.



## Step 3




- Lift off the back cover.

## Step 4



- Remove the two T6 screws.

## Step 5



- Remove the daughterboard.
- Remove the exposed vibration motor.


## Step 6 — Logic Board



- Using the T6 Torx screwdriver, remove the top screw.




## Step 7



- Using your spudger, carefully pry off back plate.
- Use the same technique as with the plastic back cover. Circle around the back plate until all of it is pried up.

## Step 8





- Remove the front cover and keypad.

## Step 9



- Remove one T6 Torx screw in the front bottom right of the board.



## Step 10



- Carefully pry the screen from the board with your spudger.
- After prying it up, remove the screen from the board.



## Step 11



- Unscrew center T6 Torx screw in the center of the logic board.
- Remove the logic board from the phone.
- Replace with new logic board.

To reassemble your device, follow these instructions in reverse order.