



# Logitech UE MegaBoom Auxiliary Port and micro USB Port Assembly Replacement

This is a guide designed to assist you in...

Written By: Oscar Ambriz



# INTRODUCTION

This is a guide designed to assist you in removing and replacing the Logitech UE Megaboom Auxiliary and USB Ports.

## TOOLS:

[Jimmy](#) (1)


[iFixit Opening Tool](#) (1)

[Tweezers](#) (1)

## Step 1 — Outer Mesh




- Locate the ends of the speaker.
- Put a plastic opening tool in-between the rubber end and the mesh.
- Apply a upward force in order to pry open the end.
- Apply this procedure to the other side as well.

 Will take force.

 Using metal tools may permanently mar your device.

## Step 2



- Take the Jimmy and pry up the rubber strip that has the volume buttons on it.
- ① You will hear clicks as it pries up, don't worry.
- Remove all the rubber you pried off.

## Step 3



- Use [tweezers](#) to lift end of plastic retainer on edge of mesh out of its channel.
  - Work the plastic retainer out of the channel all the way around the speaker.
- ⚠ Be gentle, it is easy to damage the fabric.
- Repeat for other side.

## Step 4 — Auxiliary Port and micro USB Port



- Apply an upward force with your thumbs to loosen the end cap.
- Grasp the end cap and lift up to separate it from the base.

## Step 5



- Use [tweezers](#) or an opening tool to remove the plastic insert on the inside of the rubber seal.
- Push up on the rectangular connector from the bottom to loosen the circuit board.



## Step 6



- Now grasp the plastic on the outside of the rubber seal and pull it out by applying an upward force.
  - Once the plastic has been removed, pull out the circuit board containing the auxiliary and USB ports.
- 

To reassemble your device, follow these instructions in reverse order.